terxon.®

AZ4130

Terxon MX 8–zone Wired Extension

The Terxon MX 8–zone Wired Extension is an extension module for the Terxon MX. Using this module, you can extend your alarm system by up to 8 wired alarm zones.
The 8 zones of the wired expansion are connected to the motherboard of the Terxon MX via 4–wire bus cables. You can connect up to 3 expansion modules (wireless or wired) to your existing alarm center. The Terxon MX can thus be expanded to up to 32 zones.
The additional alarm zones are freely programmable and tampering–protected. The type of wiring – NC or DEOL – is left up to you, but it must be the same for all zones. Via a jumper on the circuit board, you can assign the zones of the expansion module (9 to 16, 17 to 24 and 25 to
32).

Product highlights:

- Extends Terxon MX by 8 wired zones
- Simple connection with 4–wire bus
- Allows individual identification of detectors (recommended in sensitive areas)
- Allows clustering into logical areas
- Minimizes wiring effort

© 2012 ABUS Security–Center GmbH & Co. KG, Errors and omissions excepted.

terxon.®

AZ4130

Terxon MX 8–zone Wired Extension

Technical Data	
Connection	4–wire bus
Wiring	NC or DEOL (FSL)
Zones	8
Operating voltage	12 V
Current consumption	max. 30 mA
Weight	342 g
Dimensions (WxHxD)	128x183x35 mm

© 2012 ABUS Security–Center GmbH & Co. KG, Errors and omissions excepted.